

GSM independent Multi-function alarm

User Manual

This product use military technology GSM module with mutlti sensor components, also have remote sound pickup funtion, can be installed in home, companies,shops and warehouse, this product compact size, voice clear, long standby time, simple operation, stable performance, without install, remote control etc.,

Product view:

Past the host and magnet box on door and door can, it is ok.



Usage:

Boot: The SIM card inserted into the card connector, and then pull the switch to "on" position, the red indicator light after 30 seconds the product is ready. This state can answer an incoming call,

funtion Settings:

Send **GDM1** start voice control,when sound around ,the product will call your mobile.

Send **GDM2** stop voice control.

Send **GDM3** inquire electric quantity.

Send **GDM4** start magnetic sensor control,when the door was opened or closed ,the product will sent SMS to you and call your mobile.

Send **GDM5** stop magnetic sensor control.

Send **SJ**** set voice control call back interval.

Send **MY** report GSM base station ID information. Inquires the map information please visit: www.trackanywhere.org

* send **CALL** set remind way as make a call.

* send **SMS** set remind way as send a SMS. (please careful use these two function, once set ,you can only 2 Select 1,only make a call or only send a SMS).

Note:

* This machine is only inserted the SIM can be boot.

* Please pull the swich "on" position. when charge.

* The new machines need to be recharged 2-3 hours before first use. Please use our distribute charger to protect host.

* Standby time: 100-150 hours . depending on the local network signal strength may be.

* if the product can't Auto-Answer: To confirm whether the GSM card, this machine using a GSM network. View cell phone phone signal is strong enough to install location.

Network type:

GSM900MHz/DCS1800MHz

Accessories:

Host 1

Magnet bos 1

Charger 1

USB Charging Cable 1